


lenovo

IdeaPad U160/U165

Hardware Maintenance Manual



Note:

Before using this information and the product it supports, be sure to read the general information under "Notices" on page 76.

First Edition (April 2010)

© Copyright Lenovo 2010. All rights reserved.

LENOVO products, data, computer software, and services have been developed exclusively at private expense and are sold to governmental entities as commercial items as defined by 48 C.F.R. 2.101 with limited and restricted rights to use, reproduction and disclosure.

LIMITED AND RESTRICTED RIGHTS NOTICE: If products, data, computer software, or services are delivered pursuant a General Services Administration "GSA" contract, use, reproduction, or disclosure is subject to restrictions set forth in Contract No. GS-35F-05925.

© 2010 Lenovo

Contents

About this manual	iv	1070 LCD unit.....	44
Safety information	1	1080 Hard disk drive (HDD).....	46
General safety	2	1090 DIMM	47
Electrical safety	3	1100 Fan assembly and heat sink assembly.....	48
Safety inspection guide	5	1110 System board	50
Handling devices that are sensitive to electrostatic discharge.....	6	1120 Speakers.....	53
Grounding requirements.....	6	1130 Bluetooth card.....	54
Safety notices: multilingual translations.....	7	1140 LCD front bezel.....	55
Laser compliance statement.....	14	1150 LCD panel, LCD cable and hinges.....	56
Important service information.....	16	1160 Integrated camera.....	58
Strategy for replacing FRUs	16	1170 Antenna assembly and LCD cover	59
Strategy for replacing a hard disk drive	17	Locations	60
Important notice for replacing a system board	17	Front view	60
Important information about replacing RoHS compliant FRUs	18	Right-side view	61
General checkout	19	Bottom and Left-side view	61
What to do first	20	Parts list.....	62
Power system checkout.....	21	Overall	63
Checking the AC adapter	21	LCD FRUs	67
Checking operational charging	21	Keyboard	69
Checking the battery pack	22	Miscellaneous parts.....	72
Related service information	23	AC adapters.....	73
Restoring the factory contents by using		Power cords.....	74
OneKey Recovery	23	Notices.....	76
Restore of factory default	23	Trademarks	77
Using recovery discs.....	23		
Passwords	24		
Power-on password	24		
Supervisor password	24		
Power management	25		
Screen blank mode.....	25		
Sleep (standby) mode	25		
Hibernation mode	26		
Lenovo IdeaPad U160/U165.....	27		
Specifications	27		
Status indicators.....	29		
Fn key combinations.....	31		
FRU replacement notices	32		
Screw notices	32		
Removing and replacing an FRU	33		
1010 Battery pack.....	34		
1020 Dummy card	35		
1030 SIM card	36		
1040 Keyboard	37		
1050 Base cover.....	39		
1060 PCI Express Mini Card for wireless LAN/WAN	42		

About this manual

This manual contains service and reference information for the following Lenovo IdeaPad product:

Lenovo IdeaPad U160/U165

Use this manual to troubleshoot problems.

The manual is divided into the following sections:

- The common sections provide general information, guidelines, and safety information required for servicing computers.
- The product-specific section includes service, reference, and product-specific parts information.

Important:

This manual is intended only for trained servicers who are familiar with Lenovo IdeaPad products. Use this manual to troubleshoot problems effectively.

Before servicing a Lenovo IdeaPad product, make sure to read all the information under “Safety information” on page 1 and “Important service information” on page 16.

Safety information

This chapter presents the following safety information that you need to get familiar with before you service an IdeaPad U160/U165 computer:

- “General safety” on page 2
- “Electrical safety” on page 3
- “Safety inspection guide” on page 5
- “Handling devices that are sensitive to electrostatic discharge” on page 6
- “Grounding requirements” on page 6
- “Safety notices: multilingual translations” on page 7
- “Laser compliance statement” on page 14

General safety

Follow these rules below to ensure general safety:

- Observe a good housekeeping in the area where the machines are put during and after the maintenance.
- When lifting any heavy object:
 1. Make sure that you can stand safely without slipping.
 2. Distribute the weight of the object equally between your feet.
 3. Use a slow lifting force. Never move suddenly or twist when you attempt to lift it.
 4. Lift it by standing or pushing up with your leg muscles; this action could avoid the strain from the muscles in your back. Do not attempt to lift any object that weighs more than 16 kg (35 lb) or that you think is too heavy for you.
- Do not perform any action that causes hazards to the customer, or that makes the machine unsafe.
- Before you start the machine, make sure that other service representatives and the customer are not in a hazardous position.
- Place removed covers and other parts in a safe place, keeping them away from all personnel, while you are servicing the machine.
- Keep your toolcase away from walk areas so that other people will not trip it over.
- Do not wear loose clothing that can be trapped in the moving parts of the machine. Make sure that your sleeves are fastened or rolled up above your elbows. If your hair is long, fasten it.
- Insert the ends of your necktie or scarf inside clothing or fasten it with the nonconductive clip, about 8 centimeters (3 inches) from the end.
- Do not wear jewelry, chains, metal-frame eyeglasses, or metal fasteners for your clothing.

Attention: Metal objects are good electrical conductors.
- Wear safety glasses when you are hammering, drilling, soldering, cutting wire, attaching springs, using solvents, or working in any other conditions that may be hazardous to your eyes.
- After service, reinstall all safety shields, guards, labels, and ground wires. Replace any safety device that is worn or defective.
- Reinstall all covers correctly before returning the machine to the customer.
- Fan louvers on the machine help to prevent the overheating of internal components. Do not obstruct fan louvers or cover them with labels or stickers.

Electrical safety

Observe the following rules when working on electrical equipments.

Important:

Use only approved tools and test equipments. Some hand tools have handles covered with a soft material that does not insulate you when working with live electrical currents.

Many customers have rubber floor mats near their machines that contain small conductive fibers to decrease electrostatic discharges. Do not use such kind of mat to protect yourself from electrical shock.

- Find the room emergency power-off (EPO) switch, disconnecting the switch or electrical outlet. If an electrical accident occurs, you can then operate the switch or unplug the power cord quickly.
- Do not work alone under hazardous conditions or near the equipment that has hazardous voltages.
- Disconnect all power before:
 - Performing a mechanical inspection
 - Working near power supplies
 - Removing or installing main units
- Before you start to work on the machine, unplug the power cord. If you cannot unplug it, ask the customer to power-off the wall box that supplies power to the machine, and to lock the wall box in the off position.
- If you need to work on a machine that has exposed electrical circuits, observe the following precautions:
 - Ensure that another person, familiar with the power-off controls, is near you.

Attention: Another person must be there to switch off the power, if necessary.
 - Use only one hand when working with powered-on electrical equipment; keep the other hand in your pocket or behind your back.

Attention: An electrical shock can occur only when there is a complete circuit. By observing the above rule, you may prevent a current from passing through your body.
 - When using testers, set the controls correctly and use the approved probe leads and accessories for that tester.
 - Stand on suitable rubber mats (obtained locally, if necessary) to insulate you from grounds such as metal floor strips and machine frames.

Observe the special safety precautions when you work with very high voltages; instructions for these precautions are in the safety sections of maintenance information. Be extremely careful when you measure the high voltages.

- Regularly inspect and maintain your electrical hand tools for safe operational condition.
- Do not use worn or broken tools and testers.
- Never assume that power has been disconnected from a circuit. First, check it to make sure that it has been powered off.

- Always look carefully for possible hazards in your work area. Examples of these hazards are moist floors, nongrounded power extension cables, power surges, and missing safety grounds.
- Do not touch live electrical circuits with the reflective surface of a plastic dental mirror. The surface is conductive; such touching can cause personal injury and machine damage.
- Do not service the following parts with the power on when they are removed from their normal operating places in a machine:
 - Power supply units
 - Pumps
 - Blowers and fans
 - Motor generatorsand similar units. (This practice ensures correct grounding of the units.)
- If an electrical accident occurs:
 - Caution: do not become a victim yourself.
 - Switch off the power.
 - Send the victim to get medical aid.

Safety inspection guide

The purpose of this inspection guide is to assist you in identifying potential unsafe conditions. As each machine was designed and built, required safety items were installed to protect users and service personnel from injury. This guide addresses only those items. You should use good judgment to identify potential safety hazards according to the attachment of non-Lenovo IdeaPad features or options not covered by this inspection guide.

If any unsafe conditions are present, you must determine how serious the apparent hazard could be and whether you can continue without first correcting the problem.

Consider these conditions and the safety hazards they present:

- Electrical hazards, especially primary power (primary voltage on the frame can cause serious or fatal electrical shock)
- Explosive hazards, such as a damaged CRT face or a bulging capacitor
- Mechanical hazards, such as loose or missing hardware

To determine whether there are any potential unsafe conditions, use the following checklist at the beginning of every service task. Begin the checks with the power off, and the power cord disconnected.

Checklist:

1. Check exterior covers for damage (loose, broken, or sharp edges).
2. Turn off the computer. Disconnect the power cord.
3. Check the power cord for:
 - a. A third-wire ground connector in good condition. Use a meter to measure third-wire ground continuity for 0.1 ohm or less between the external ground pin and the frame ground.
 - b. The power cord should be the type specified in the parts list.
 - c. Insulation must not be frayed or worn.
4. Check for cracked or bulging batteries.
5. Remove the cover.
6. Check for any obvious non-Lenovo IdeaPad alterations. Use good judgment as to the safety of any non-Lenovo IdeaPad alterations.
7. Check inside the unit for any obvious unsafe conditions, such as metal filings, contamination, water or other liquids, or signs of fire or smoke damage.
8. Check for worn, frayed, or pinched cables.
9. Check that the power-supply cover fasteners (screws or rivets) have not been removed or tampered with.

Handling devices that are sensitive to electrostatic discharge

Any computer part containing transistors or integrated circuits (ICs) should be considered sensitive to electrostatic discharge (ESD). ESD damage can occur when there is a difference in charge between objects. Protect against ESD damage by equalizing the charge so that the machine, the part, the work mat, and the person handling the part are all at the same charge.

Notes:

1. Use product-specific ESD procedures when they exceed the requirements noted here.
2. Make sure that the ESD protective devices you use have been certified (ISO 9000) as fully effective.

When handling ESD-sensitive parts:

- Keep the parts in protective packages until they are inserted into the product.
- Avoid contact with other people.
- Wear a grounded wrist strap against your skin to eliminate static on your body.
- Prevent the part from touching your clothing. Most clothing is insulative and retains a charge even when you are wearing a wrist strap.
- Use the black side of a grounded work mat to provide a static-free work surface. The mat is especially useful when handling ESD-sensitive devices.
- Select a grounding system, such as those listed below, to provide protection that meets the specific service requirement.

Note:

The use of a grounding system to guard against ESD damage is desirable but not necessary.

- Attach the ESD ground clip to any frame ground, ground braid, or green-wire ground.
- When working on a double-insulated or battery-operated system, use an ESD common ground or reference point. You can use coax or connector-outside shells on these systems.
- Use the round ground prong of the ac plug on ac-operated computers.

Grounding requirements

Electrical grounding of the computer is required for operator safety and correct system function. Proper grounding of the electrical outlet can be verified by a certified electrician.

Safety notices: multilingual translations

The safety notices in this section are provided in English, French, German, Hebrew, Italian, Japanese, and Spanish.

Safety notice 1

Before the computer is powered on after FRU replacement, make sure all screws, springs, and other small parts are in place and are not left loose inside the computer. Verify this by shaking the computer and listening for rattling sounds. Metallic parts or metal flakes can cause electrical shorts.

Avant de remettre l'ordinateur sous tension après remplacement d'une unité en clientèle, vérifiez que tous les ressorts, vis et autres pièces sont bien en place et bien fixées. Pour ce faire, secouez l'unité et assurez-vous qu'aucun bruit suspect ne se produit. Des pièces métalliques ou des copeaux de métal pourraient causer un court-circuit.

Bevor nach einem FRU-Austausch der Computer wieder angeschlossen wird, muß sichergestellt werden, daß keine Schrauben, Federn oder andere Kleinteile fehlen oder im Gehäuse vergessen wurden. Der Computer muß geschüttelt und auf Klappergeräusche geprüft werden. Metallteile oder-splitter können Kurzschlüsse erzeugen.

לפני הפעלת המחשב לאחר החלפת FRU יש לוודא שכל הברגים, הקפיצים, וחלקים קטנים אחרים נמצאים במקומם ואינם חופשיים לזוז בתוך המחשב. כדי לוודא זאת, יש לטלטל את המחשב ולהקשיב לגילוי קולות שקשוק. חלקיקי או שבבי מתכת עלולים לגרום לקצרים חשמליים.

Prima di accendere l'elaboratore dopo che é stata effettuata la sostituzione di una FRU, accertarsi che tutte le viti, le molle e tutte le altri parti di piccole dimensioni siano nella corretta posizione e non siano sparse all'interno dell'elaboratore. Verificare ciò scuotendo l'elaboratore e prestando attenzione ad eventuali rumori; eventuali parti o pezzetti metallici possono provocare cortocircuiti pericolosi.

FRUの交換後、コンピュータの電源を入れる前に、ねじ、バネ、その他の小さな部品がすべて正しい位置にあり、またコンピュータの内部で緩んでいないことを確認してください。これを確認するには、コンピュータを振って、カチャカチャと音がしないか確かめます。金属部品や金属破片はショートの原因になることがあります。

Antes de encender el sistema despues de sustituir una FRU, compruebe que todos los tornillos, muelles y demás piezas pequeñas se encuentran en su sitio y no se encuentran sueltas dentro del sistema. Compruébelo agitando el sistema y escuchando los posibles ruidos que provocarían. Las piezas metálicas pueden causar cortocircuitos eléctricos.

Safety notice 2

⚠ DANGER

Some standby batteries contain a small amount of nickel and cadmium. Do not disassemble a standby battery, recharge it, throw it into fire or water, or short-circuit it. Dispose of the battery as required by local ordinances or regulations. Use only the battery in the appropriate parts listing. Use of an incorrect battery can result in ignition or explosion of the battery.

Certaines batteries de secours contiennent du nickel et du cadmium. Ne les démontez pas, ne les rechargez pas, ne les exposez ni au feu ni à l'eau. Ne les mettez pas en court-circuit. Pour les mettre au rebut, conformez-vous à la réglementation en vigueur. Lorsque vous remplacez la pile de sauvegarde ou celle de l'horloge temps réel, veillez à n'utiliser que les modèles cités dans la liste de pièces détachées adéquate. Une batterie ou une pile inappropriée risque de prendre feu ou d'exploser.

Die Bereitschaftsbatterie, die sich unter dem Diskettenlaufwerk befindet, kann geringe Mengen Nickel und Cadmium enthalten. Sie darf nicht zerlegt, wiederaufgeladen, kurzgeschlossen, oder Feuer oder Wasser ausgesetzt werden. Bei der Entsorgung die örtlichen Bestimmungen für Sondermüll beachten. Beim Ersetzen der Bereitschafts- oder Systembatterie nur Batterien des Typs verwenden, der in der Ersatzteilliste aufgeführt ist. Der Einsatz falscher Batterien kann zu Entzündung oder Explosion führen.

סוללות המתנה מסוימות מכילות כמות קטנה של ניקל וקדמיום. אין לפרק סוללת המתנה, לטעון אותה מחדש, להשליך אותה לאש או למים או לקצר אותה. יש לשלוק את הסוללה כנדרש על ידי התקנות והחוקים המקומיים. יש להשתמש רק בסוללה המופיעה ברשימת החלקים המתאימה. שימוש בסוללה לא מתאימה עלול לגרום להצתה או התפוצצות של הסוללה.

Alcune batterie di riserva contengono una piccola quantità di nichel e cadmio. Non smontarle, ricaricarle, gettarle nel fuoco o nell'acqua né cortocircuitarle. Smaltirle secondo la normativa in vigore (DPR 915/82, successive disposizioni e disposizioni locali). Quando si sostituisce la batteria dell'RTC (real time clock) o la batteria di supporto, utilizzare soltanto i tipi inseriti nell'appropriato Catalogo parti. L'impiego di una batteria non adatta potrebbe determinare l'incendio o l'esplosione della batteria stessa.

予備バッテリーの中には少量のニッケルとカドミウムが含まれているものがあります。したがって、予備バッテリーの分解、再充電、火または水の中への投棄、またはショートさせることは決して行わないでください。バッテリーを廃棄する場合は地方自治体の条例に従ってください。適切なパーツ・リストにあるバッテリーだけを使用してください。誤ったバッテリーを使用すると、バッテリーが発火したり、爆発したりすることがあります。

Algunas baterías de reserva contienen una pequeña cantidad de níquel y cadmio. No las desmonte, ni recargue, ni las eche al fuego o al agua ni las cortocircuite. Deséchelas tal como dispone la normativa local. Utilice sólo baterías que se encuentren en la lista de piezas. La utilización de una batería no apropiada puede provocar la ignición o explosión de la misma.

Safety notice 3**⚠ DANGER**

The battery pack contains small amounts of nickel. Do not disassemble it, throw it into fire or water, or short-circuit it. Dispose of the battery pack as required by local ordinances or regulations. Use only the battery in the appropriate parts listing when replacing the battery pack. Use of an incorrect battery can result in ignition or explosion of the battery.

La batterie contient du nickel. Ne la démontez pas, ne l'exposez ni au feu ni à l'eau. Ne la mettez pas en court-circuit. Pour la mettre au rebut, conformez-vous à la réglementation en vigueur. Lorsque vous remplacez la batterie, veillez à n'utiliser que les modèles cités dans la liste de pièces détachées adéquate. En effet, une batterie inappropriée risque de prendre feu ou d'exploser.

Akkus enthalten geringe Mengen von Nickel. Sie dürfen nicht zerlegt, wiederaufgeladen, kurzgeschlossen, oder Feuer oder Wasser ausgesetzt werden. Bei der Entsorgung die örtlichen Bestimmungen für Sondermüll beachten. Beim Ersetzen der Batterie nur Batterien des Typs verwenden, der in der Ersatzteilliste aufgeführt ist. Der Einsatz falscher Batterien kann zu Entzündung oder Explosion führen.

מארו הסוללה מכיל כמות קטנה של ניקל
וקדמיום. אין לפרק את מארו הסוללה, להשליך
אותו לאש או למים או לקצר אותו. יש לסלק את
מארו הסוללה הסוללה כנדרש על ידי התקנות
והחוקים המקומיים. יש להשתמש רק בסוללה
המופיעה ברשימת החלקים המתאימה בזמן החלפת
מארו הסוללה. שימוש בסוללה לא מתאימה עלול
לגרום לתוצאה או התפוצצות של הסוללה.

La batteria contiene piccole quantità di nichel. Non smontarla, gettarla nel fuoco o nell'acqua né cortocircuitarla. Smaltirla secondo la normativa in vigore (DPR 915/82, successive disposizioni e disposizioni locali). Quando si sostituisce la batteria, utilizzare soltanto i tipi inseriti nell'appropriato Catalogo parti. L'impiego di una batteria non adatta potrebbe determinare l'incendio o l'esplosione della batteria stessa.

バッテリー・パックには少量のニッケルが含まれています。バッテリー・パックを分解したり、火または水の中に投げ込んだり、ショートさせないでください。バッテリー・パックの廃棄にあたっては、地方自治体の条例または規則に従ってください。バッテリー・パックを交換するときは、適切なパーツ・リストにあるバッテリーだけを使用してください。誤ったバッテリーを使用すると、バッテリーが発火したり、爆発したりすることがあります。

Las baterías contienen pequeñas cantidades de níquel. No las desmonte, ni recargue, ni las eche al fuego o al agua ni las cortocircuite. Deséchelas tal como dispone la normativa local. Utilice sólo baterías que se encuentren en la lista de piezas al sustituir la batería. La utilización de una batería no apropiada puede provocar la ignición o explosión de la misma.

Safety notice 4

⚠ DANGER

The lithium battery can cause a fire, an explosion, or a severe burn. Do not recharge it, remove its polarized connector, disassemble it, heat it above 100°C (212°F), incinerate it, or expose its cell contents to water. Dispose of the battery as required by local ordinances or regulations. Use only the battery in the appropriate parts listing. Use of an incorrect battery can result in ignition or explosion of the battery.

La pile de sauvegarde contient du lithium. Elle présente des risques d'incendie, d'explosion ou de brûlures graves. Ne la rechargez pas, ne retirez pas son connecteur polarisé et ne la démontez pas. Ne l'exposez pas à une température supérieure à 100°C, ne la faites pas brûler et n'en exposez pas le contenu à l'eau. Mettez la pile au rebut conformément à la réglementation en vigueur. Une pile inappropriée risque de prendre feu ou d'exploser.

Die Systematterie ist eine Lithiumatterie. Sie kann sich entzünden, explodieren oder schwere Verbrennungen hervorrufen. Batterien dieses Typs dürfen nicht aufgeladen, zerlegt, über 100 C erhitzt oder verbrannt werden. Auch darf ihr Inhalt nicht mit Wasser in Verbindung gebracht oder der zur richtigen Polung angebrachte Verbindungsstecker entfernt werden. Bei der Entsorgung die örtlichen Bestimmungen für Sondermüll beachten. Beim Ersetzen der Batterie nur Batterien des Typs verwenden, der in der Ersatzteilliste aufgeführt ist. Der Einsatz falscher Batterien kann zu Entzündung oder Explosion führen.

סוללת הליתיום עלולה לגרום לשריפה, להתפוצצות או לכוויות קשות. אין לטעון אותה מחדש, לסלק את המחבר המקושר שלה, לפרק אותה או לחמם אותה בטמפרטורה העולה על 100 מעלות צלזיוס. אין לשרוף את הסוללה ואין לחשוף את תוכן התא למים. יש לסלק את הסוללה בנדרש בתקנות ובחוקים המקומיים. יש להשתמש רק בסוללה המומינה ברשימת החלקים המתאימים. שימוש בסוללה אחרת עלול לגרום לשכנת שריפה או התפוצצות.

La batteria di supporto e una batteria al litio e puo incendiarsi, esplodere o procurare gravi ustioni. Evitare di ricaricarla, smontarne il connettore polarizzato, smontarla, riscaldarla ad una temperatura superiore ai 100 gradi centigradi, incendiarla o gettarla in acqua. Smaltirla secondo la normativa in vigore (DPR 915/82, successive disposizioni e disposizioni locali). L'impiego di una batteria non adatta potrebbe determinare l'incendio o l'esplosione della batteria stessa.

リチウム・バッテリーは、火災、爆発、または重症のやけどを引き起こすことがあります。バックアップ・バッテリーの充電、その極性コネクタの取り外し、バッテリー本体の分解、100℃(212°F)以上の加熱、焼却、電池の中身を水に浸すことはしないでください。バッテリーを廃棄する場合は地方自治体の条例に従ってください。適切なパーツ・リストにあるバッテリーだけを使用してください。誤ったバッテリーを使用すると、バッテリーが発火したり、爆発したりすることがあります。

La batería de repuesto es una batería de litio y puede provocar incendios, explosiones o quemaduras graves. No la recargue, ni quite el conector polarizado, ni la desmonte, ni caliente por encima de los 100°C (212°F), ni la incinere ni exponga el contenido de sus celdas al agua. Deséchela tal como dispone la normativa local.

Safety notice 5

If the LCD breaks and the fluid from inside the LCD gets into your eyes or on your hands, immediately wash the affected areas with water at least for 15 minutes. Seek medical care if any symptoms caused by the fluid are present after washing.

Si le panneau d'affichage à cristaux liquides se brise et que vous recevez dans les yeux ou sur les mains une partie du fluide, rincez-les abondamment pendant au moins quinze minutes. Consultez un médecin si des symptômes persistent après le lavage.

Die Leuchtstoffröhre im LCD-Bildschirm enthält Quecksilber. Bei der Entsorgung die örtlichen Bestimmungen für Sondermüll beachten. Der LCD-Bildschirm besteht aus Glas und kann zerbrechen, wenn er unsachgemäß behandelt wird oder der Computer auf den Boden fällt. Wenn der Bildschirm beschädigt ist und die darin befindliche Flüssigkeit in Kontakt mit Haut und Augen gerät, sollten die betroffenen Stellen mindestens 15 Minuten mit Wasser abgespült und bei Beschwerden anschließend ein Arzt aufgesucht werden.

אם מסך הנביש הנוזלי (LCD) נשבר והנוזל מתוך המסך בא במגע עם עיניים או ידיים, שטפו את האזורים הנגועים מיד במים במשך 15 דקות לפחות. פנו לקבלת עזרה רפואית אם תסמינים הנובעים מהמגע עם הנוזל נמשכים לאחר השטיפה.

Nel caso che caso l'LCD si dovesse rompere ed il liquido in esso contenuto entrasse in contatto con gli occhi o le mani, lavare immediatamente le parti interessate con acqua corrente per almeno 15 minuti; poi consultare un medico se i sintomi dovessero permanere.

LCD が破損し、LCD 中の液体が目に入ったり、手に触れたりした場合は、液体が触れた部分を少なくとも 15 分間洗い流してください。洗い流した後に、液体によって何らかの症状が現れた場合は、医師の治療を受けてください。

Si la LCD se rompe y el fluido de su interior entra en contacto con sus ojos o sus manos, lave inmediatamente las áreas afectadas con agua durante 15 minutos como mínimo. Obtenga atención medica si se presenta algún sintoma del fluido despues de lavarse.

Safety notice 6

⚠ DANGER

To avoid shock, do not remove the plastic cover that protects the lower part of the inverter card.

Afin d'éviter tout risque de choc électrique, ne retirez pas le cache en plastique protégeant la partie inférieure de la carte d'alimentation.

Aus Sicherheitsgründen die Kunststoffabdeckung, die den unteren Teil der Spannungswandlerplatine umgibt, nicht entfernen.

כדי למנוע התחשמלות, אין להסיר את מכסה הפלסטיק המגן על חלקו התחתון של הכרטיס ההפוך.

Per evitare scosse elettriche, non rimuovere la copertura in plastica che avvolge la parte inferiore della scheda invertitore.

感電を防ぐため、インバーター・カードの下部を保護しているプラスチック・カバーを外さないでください。

Para evitar descargas, no quite la cubierta de plástico que rodea la parte baja de la tarjeta invertida.

Safety notice 7

⚠ DANGER

Though the main batteries have low voltage, a shorted or grounded battery can produce enough current to burn personnel or combustible materials.

Bien que le voltage des batteries principales soit peu élevé, le court-circuit ou la mise à la masse d'une batterie peut produire suffisamment de courant pour brûler des matériaux combustibles ou causer des brûlures corporelles graves.

Obwohl Hauptbatterien eine niedrige Spannung haben, können sie doch bei Kurzschluß oder Erdung genug Strom abgeben, um brennbare Materialien zu entzünden oder Verletzungen bei Personen hervorzurufen.

אף שהסוללות הראשיות הן בעלות מתח נמוך, סוללה מקוצרת או מוארזת עלולה להפיק זרם מספיק לגרימת כוויות או להצתת חומרים דליקים.

Sebbene le batterie di alimentazione siano a basso voltaggio, una batteria in corto circuito o a massa può fornire corrente sufficiente da bruciare materiali combustibili o provocare ustioni ai tecnici di manutenzione.

メイン・バッテリーの電圧は低くても、ショートしたり、接地したバッテリーが、作業者にやけどを負わせたり、可燃物を燃やすだけの電流を発生させる場合があります。

Aunque las baterías principales tienen un voltaje bajo, una batería cortocircuitada o con contacto a tierra puede producir la corriente suficiente como para quemar material combustible o provocar quemaduras en el personal.

Safety notice 8

DANGER

Before removing any FRU, turn off the computer, unplug all power cords from electrical outlets, remove the battery pack, and then disconnect any interconnecting cables.

Avant de retirer une unité remplaçable en clientèle, mettez le système hors tension, débranchez tous les cordons d'alimentation des socles de prise de courant, retirez la batterie et déconnectez tous les cordons d'interface.

Die Stromzufuhr muß abgeschaltet, alle Stromkabel aus der Steckdose gezogen, der Akku entfernt und alle Verbindungskabel abgenommen sein, bevor eine FRU entfernt wird.

לפני סילוק FRU כלשהו, יש לכבות את המחשב,
לנתק את כל כבלי החשמל משקעי החשמל, להוציא
את מארז הסוללה, ואז לנתק כבלי חיבור אחרים
אם יש כאלה.

Prima di rimuovere qualsiasi FRU, spegnere il sistema, scollegare dalle prese elettriche tutti i cavi di alimentazione, rimuovere la batteria e poi scollegare i cavi di interconnessione.

FRU を取り外す前に、ThinkPad の電源を切って、すべての電源コードをコンセントから外してください。次に、バッテリー・パックを外し、相互接続ケーブルを外してください。

Antes de quitar una FRU, apague el sistema, desenchufe todos los cables de las tomas de corriente eléctrica, quite la batería y, a continuación, desconecte cualquier cable de conexión entre dispositivos.

Laser compliance statement

Some models of Lenovo IdeaPad computer are equipped from the factory with an optical storage device such as a CD-ROM drive or a DVD-ROM drive. Such devices are also sold separately as options. If one of these drives is installed, it is certified in the U.S. to conform to the requirements of the Department of Health and Human Services 21 Code of Federal Regulations (DHHS 21 CFR) Subchapter J for Class 1 laser products. Elsewhere, the drive is certified to conform to the requirements of the International Electrotechnical Commission (IEC) 825 and CENELEC EN 60 825 for Class 1 laser products.

If a CD-ROM drive, a DVD-ROM drive, or another laser device is installed, note the following:

CAUTION

Use of controls or adjustments or performance of procedures other than those specified herein might result in hazardous radiation exposure.

O uso de controles, ajustes ou desempenho de procedimentos diferentes daqueles aqui especificados pode resultar em perigosa exposição à radiação.

凡未在这里指明的任何控制用法、调整、行为，都会导致严重后果。

Pour éviter tout risque d'exposition au rayon laser, respectez les consignes de réglage et d'utilisation des commandes, ainsi que les procédures décrites.

Werden Steuer- und Einstellelemente anders als hier festgesetzt verwendet, kann gefährliche Laserstrahlung auftreten.

Az itt előírt eljárásoktól, beállításoktól és vezérlésektől eltérni a lézersugárzás veszélye miatt kockázatos!

L'utilizzo di controlli, regolazioni o l'esecuzione di procedure diverse da quelle specificate possono provocare l'esposizione a.

Использование элементов настройки и выполнение процедур иных, чем указано здесь, может привести к опасному радиационному облучению.

Použitie kontrol, úprav alebo iných vykonaní od iných výrobcov, ako je v tomto špecifikované, mohlo by mať za následok nebezpečenstvo vystavenia sa vyžiarovaniu.

本書で指定された内容以外のお客様による整備、調整、または手順を行った場合、レーザー光の放射の危険があります。

El uso de controles o ajustes o la ejecución de procedimientos distintos de los aquí especificados puede provocar la exposición a radiaciones peligrosas.

Opening the CD-ROM drive, the DVD-ROM drive, or any other optical storage device could result in exposure to hazardous laser radiation. There are no serviceable parts inside those drives. **Do not open.**

A CD-ROM drive, a DVD-ROM drive, or any other storage device installed may contain an embedded Class 3A or Class 3B laser diode. Note the following:

⚠ DANGER

Emits visible and invisible laser radiation when open. Do not stare into the beam, do not view directly with optical instruments, and avoid direct exposure to the beam.

Radiação por raio laser ao abrir. Não olhe fixo no feixe de luz, não olhe diretamente por meio de instrumentos óticos e evite exposição direta com o feixe de luz.

开启时会有激光发射时，请勿直视激光束，请勿直接查看视觉仪器，并且避免直接接触在激光束之中。

Rayonnement laser si carter ouvert. Évitez de fixer le faisceau, de le regarder directement avec des instruments optiques, ou de vous exposer au rayon.

Laserstrahlung bei geöffnetem Gerät. Nicht direkt oder über optische Instrumente in den Laserstrahl sehen und den Strahlungsbereich meiden.

Kinyitáskor lézersugár ! Ne nézzen bele se szabad szemmel, se optikai eszközökkel. Kerülje a sugárnyalábbal való érintkezést!

Apriendo l'unità vengono emesse radiazioni laser. Non fissare il fascio, non guardarlo direttamente con strumenti ottici e evitare l'esposizione diretta al fascio.

Открывая, берегитесь лазерного излучения.

Не смотрите на луч, не разглядывайте его с помощью оптических инструментов, а также избегайте прямого воздействия лазерного луча.

Keď je laserová jednotka otvorená. Vyhňte sa priamemu pohľadu a nehľadte priamo s optickými nástrojmi do lúča a vyhňte sa priamemu vystaveniu lúčov.

開けるとレーザー光が放射されます。光線を見つめたり、光学機械を使って直接見たりしないでください。

Radiación láser al abrir. No mire fijamente ni examine con instrumental óptico el haz de luz. Evite la exposición directa al haz.

Important service information

This chapter presents the following important service information:

- “Strategy for replacing FRUs” on page 16
 - “Strategy for replacing a hard disk drive” on page 17
 - “Important notice for replacing a system board ” on page 17
- “Important information about replacing RoHS compliant FRUs” on page 18

Important:

BIOS and device driver fixes are customer-installable. The BIOS and device drivers are posted on the customer support site:

<http://consumersupport.lenovo.com/>.

Strategy for replacing FRUs

Before replacing parts:

Make sure that all software fixes, drivers, and BIOS downloads are installed before replacing any FRUs listed in this manual.

After a system board is replaced, ensure that the latest BIOS is loaded to the system board before completing the service action.

To download software fixes, drivers, and BIOS, follow the steps below:

1. Go to <http://consumersupport.lenovo.com/>.
2. Enter a serial number or select a product or use Lenovo smart downloading.
3. Select the BIOS/Driver/Applications and download.
4. Follow the directions on the screen and install the necessary software.

Use the following strategy to prevent unnecessary expense for replacing and servicing FRUs:

- If you are instructed to replace an FRU, but the replacement does not solve the problem, reinstall the original FRU before you continue.
- Some computers have both a processor board and a system board. If you are instructed to replace either of them, and replacing one of them does not solve the problem, reinstall that board, and then replace the other one.
- If an adapter or a device consists of more than one FRU, any of the FRUs may be the cause of the error. Before replacing the adapter or device, remove the FRUs one by one to see if the symptoms change. Replace only the FRU that changed the symptoms.

Attention: The setup configuration on the computer you are servicing may have been customized. Running Automatic Configuration may alter the settings. Note the current configuration settings (using the View Configuration option); then, when service has been completed, verify that those settings remain in effect.

Strategy for replacing a hard disk drive

Always try to run a low-level format before replacing a hard disk drive. This will cause all customer data on the hard disk to be lost. Make sure that the customer has a current backup of the data before performing this action.

Attention: The drive startup sequence in the computer you are servicing may have been changed. Be extremely careful during write operations such as copying, saving, or formatting. If you select an incorrect drive, data or programs can be overwritten.

Important notice for replacing a system board

Some components mounted on a system board are very sensitive. Improper handling can cause damage to those components, and may cause a system malfunction.

Attention: When handling a system board:

- Do not drop the system board or apply any excessive force to it.
- Avoid rough handling of any kind.
- Avoid bending the system board and hard pushing to prevent cracking at each BGA (Ball Grid Array) chipset.

Important information about replacing RoHS compliant FRUs

RoHS, The Restriction of Hazardous Substances in Electrical and Electronic Equipment Directive (2002/95/EC) is a European Union legal requirement affecting the global electronics industry. RoHS requirements must be implemented on Lenovo products placed on the market after June 2006. Products on the market before June 2006 are not required to have RoHS compliant parts. If the original FRU parts are non-compliant, replacement parts can also be non-compliant. In all cases if the original FRU parts are RoHS compliant, the replacement part must also be RoHS compliant.

Note: RoHS and non-RoHS FRU part numbers with the same fit and function are identified with unique FRU part numbers.

Lenovo plans to transit to RoHS compliance well before the implementation date and expects its suppliers to be ready to support Lenovo's requirements and schedule in the EU. Products sold in 2005 and 2006 will contain some RoHS compliant FRUs. The following statement pertains to these products and any product Lenovo produces containing RoHS compliant FRUs.

RoHS compliant FRUs have unique FRU part numbers. Before or after the RoHS implementation date, failed RoHS compliant parts must always be replaced with RoHS compliant ones, so only the FRUs identified as compliant in the system HMM or direct substitutions for those FRUs may be used.

Products marketed before June 2006		Products marketed after June 2006	
Current or original part	Replacement FRU	Current or original part	Replacement FRU
Non-RoHS	Can be Non-RoHS	Must be RoHS	Must be RoHS
Non-RoHS	Can be RoHS		
Non-RoHS	Can sub to RoHS		
RoHS	Must be RoHS		

Note: A direct substitution is a part with a different FRU part number that is automatically shipped by the distribution center at the time of the order.

General checkout

This chapter presents the following information:

- “What to do first” on page 20
- “Power system checkout” on page 21

Before you go to the checkout, make sure to read the following important notes:

Important notes:

- **Only certified trained personnel can service the computer.**
- **Before replacing any FRU, read the entire page on removing and replacing FRUs.**
- **When you replace FRUs, use new nylon-coated screws.**
- **Be extremely careful during such write operations as copying, saving, or formatting.** Drives in the computer that you are servicing sequence might have been altered. If you select an incorrect drive, data or programs might be overwritten.
- **Replace an FRU only with another FRU of the correct model.** When you replace an FRU, make sure that the machine model and the FRU part number are correct by referring to the FRU parts list.
- **An FRU should not be replaced just because of a single, unreproducible failure.** Single failures can occur for a variety of reasons that have nothing to do with a hardware defect, such as cosmic radiation, electrostatic discharge, or software errors. Consider replacing an FRU only when a problem recurs. If you suspect that an FRU is defective, clear the error logs and run the test again. If the error does not recur, do not replace the FRU.
- **Be careful not to replace a nondefective FRU.**

What to do first

When you do return an FRU, you must include the following information in the parts exchange form or parts return form that you attach to it:

1. Name and phone number of servicer
2. Date of service
3. Date on which the machine failed
4. Date of purchase
5. Procedure index and page number in which the failing FRU was detected
6. Failing FRU name and part number
7. Machine type, model number, and serial number
8. Customer's name and address

Note for warranty: During the warranty period, the customer may be responsible for repair costs if the computer damage was caused by misuse, accident, modification, unsuitable physical or operating environment, or improper maintenance by the customer.

The following is a list of some common items that are not covered under warranty and some symptoms that might indicate that the system was subjected to stress beyond normal use.

Before checking problems with the computer, determine whether the damage is covered under the warranty by referring to the following list:

The following are not covered under warranty:

- LCD panel cracked from the application of excessive force or from being dropped
- Scratched (cosmetic) parts
- Distortion, deformation, or discoloration of the cosmetic parts
- Plastic parts, latches, pins, or connectors that have been cracked or broken by excessive force
- Damage caused by liquid spilled into the system
- Damage caused by the improper insertion of a PC Card or the installation of an incompatible card
- Improper disc insertion or use of an optical drive
- Diskette drive damage caused by pressure on the diskette drive cover, foreign material in the drive, or the insertion of a diskette with multiple labels
- Damaged or bent diskette eject button
- Fuses blown by attachment of a nonsupported device
- Forgotten computer password (making the computer unusable)
- Sticky keys caused by spilling a liquid onto the keyboard
- Use of an incorrect AC adapter on laptop products

The following symptoms might indicate damage caused by nonwarranted activities:

- Missing parts might be a symptom of unauthorized service or modification.
- If the spindle of a hard disk drive becomes noisy, it may have been subjected to excessive force, or dropped.

Power system checkout

To verify a symptom, follow the steps below:

1. Turn off the computer.
2. Remove the battery pack.
3. Connect the AC adapter.
4. Make sure that power is supplied when you turn on the computer.
5. Turn off the computer.
6. Disconnect the AC adapter and install the charged battery pack.
7. Make sure that the battery pack supplies power when you turn on the computer.

If you suspect a power problem, see the appropriate one of the following power supply checkouts:

- “Checking the AC adapter ” on page 21
- “Checking operational charging” on page 21
- “Checking the battery pack ” on page 22


Checking the AC adapter

You are here because the computer fails only when the AC adapter is used.

- If the power-on indicator does not turn on, check the power cord of the AC adapter for correct continuity and installation.
- If the computer does not charge during operation, go to “Checking operational charging”.

To check the AC adapter, follow the steps below:

1. Unplug the AC adapter cable from the computer.
2. Measure the output voltage at the plug of the AC adapter cable. See the following figure:



Note: Output voltage for the AC adapter pin No. 2 may differ from the one you are servicing.

3. If the voltage is not correct, replace the AC adapter.
4. If the voltage is acceptable, do the following:
 - Replace the system board.
 - If the problem continues, go to “Lenovo IdeaPad U160/U165” on page 27.

Note: Noise from the AC adapter does not always indicate a defect.

Checking operational charging

To check whether the battery charges properly during operation, use a discharged battery pack or a battery pack that has less than 50% of the total power remaining when installed in the computer.

Perform operational charging. If the battery status indicator or icon does not light on, remove the battery pack and let it return to room temperature. Reinstall the battery pack. If the charge indicator or icon is still off, replace the battery pack.

If the charge indicator still does not light on, replace the system board. Then reinstall the battery pack. If it is still not charged, go to the next section.

Checking the battery pack


Battery charging does not start until the Power Meter shows that less than 95% of the total power remains; under this condition the battery pack can charge to 100% of its capacity. This protects the battery pack from being overcharged or from having a shortened life.

To check your battery, move your cursor to the Power Meter icon in the icon tray of the Windows® taskbar and wait for a moment (but do not click it), and the percentage of battery power remaining is displayed. To get detailed information about the battery, double-click the Power Meter icon.

Note: If the battery pack becomes hot, it may not be able to be charged. Remove it from the computer and leave it at room temperature for a while. After it cools down, reinstall and recharge it.

To check the battery pack, follow the steps below:

1. Turn off the computer.
2. Remove the battery pack and measure the voltage between battery terminals 1 (+) and 7 (-). See the following figure:



Terminal	Voltage (V DC)
1	+0 to +14
7	Ground (-)

3. If the voltage is less than +11.0 V DC, the battery pack has been discharged.

Note: Recharging will be continued for at least 3 hours, even though the indicator does not light on.

If the voltage is still less than +11.0 V DC after recharging, replace the battery.

4. If the voltage is more than +11.0 V DC, measure the resistance between battery terminals 5 and 7. The resistance must be 4 to 30 KΩ.

If the resistance is not correct, replace the battery pack. If the resistance is correct, replace the system board.

Related service information

This chapter presents the following information:

- “Restoring the factory contents by using OneKey Recovery” on page 23
- “Passwords” on page 24
- “Power management” on page 25

Restoring the factory contents by using OneKey Recovery

Restore of factory default

The IdeaPad U160/U165 computers come with pre-installed OneKey Rescue System. In order to save application files and the initial backed up files of the system, the hard disk in a Lenovo computer includes a hidden partition when it is shipped. If you need to restore the system to the point of your first boot up, just enter Lenovo OneKey Rescue System and run **Restore to factory default**. For details of OneKey Rescue System, see *the User Guide for OneKey Rescue System*.

Note: This will delete all the new data on the system partition (C drive), which is not recoverable. Make sure to back up your critical data before you perform this action.

Using recovery discs

When you replace a hard disk drive in your computer, you are unable to use the pre-installed Lenovo OneKey Recovery and OneKey Rescue. However, you can use the recovery discs that store your backed up data to restore your new hard drive to a previous backup status.

Note: You can create recovery discs by burning the backup image to a CD/DVD as recovery discs. For details of **Create recovery discs**, see *the User Guide for OneKey Rescue System*.

When you use the recovery discs to boot your computer, the system will enter the user interface for system recovery automatically. Please follow the prompt to insert the backup discs to complete the whole recovery process.

Note: The recovery process might take up to 2 hours.

Passwords

As many as two passwords may be needed for any Lenovo IdeaPad computer: the power-on password (POP) and the supervisor password (SVP).

If any of these passwords has been set, a prompt for it appears on the screen whenever the computer is turned on. The computer does not start until the password is entered.

Exception: If only an SVP is installed, the password prompt does not appear when the operating system is booted.

Power-on password

A power-on password (POP) protects the system from being powered on by an unauthorized person. The password must be entered before an operating system can be booted.

Supervisor password

A supervisor password (SVP) protects the system information stored in the BIOS Setup Utility. The user must enter the SVP in order to get access to the BIOS Setup Utility and change the system configuration.

Attention: If the SVP has been forgotten and cannot be made available to the servicer, there is no service procedure to reset the password. The system board must be replaced for a scheduled fee.

Power management

Note: Power management modes are not supported for APM operating system.

To reduce power consumption, the computer has three power management modes: screen blank, sleep (standby), and hibernation.

Screen blank mode

If the time set on the “Turn off monitor” timer in the operating system expires, the LCD backlight turns off. You can also turn off the LCD backlight by pressing Fn+F2.

To end screen blank mode and resume normal operation, press any key.

Sleep (standby) mode

When the computer enters sleep (standby) mode, the following events occur in addition to what occurs in screen blank mode:

- The LCD is powered off.
- The hard disk drive is powered off.
- The CPU stops.

To enter sleep (standby) mode, press Fn+F1.

In certain circumstances, the computer goes into sleep (standby) mode automatically:

- If a “suspend time” has been set on the timer, and the user does not do any operation with the keyboard, the hard disk, the parallel connector, or the diskette drive within that time.
- If the battery indicator starts blinking, indicating that the battery power is low. (Alternatively, if **Hibernate when battery becomes low** has been selected in the “Power Management Properties” window, the computer goes into hibernation mode.)

To cause the computer to return from sleep (standby) mode and resume the operation, do one of the following:

- Press the Fn key.
- Open the lid.
- Turn on the power switch.

Also, in the following event, the computer automatically returns from sleep (standby) mode and resumes the operation:

- The time set on the resume timer elapses.

Note: The computer does not accept any input immediately after it enters sleep (standby) mode. Wait a few seconds before taking any action to reenter operation mode.

Hibernation mode

In hibernation mode, the following occurs:

- The system status, RAM, VRAM, and setup data are stored on the hard disk.
- The system is powered off.

To cause the computer to enter hibernation mode, follow the steps below:

- If you are using the ACPI operating system and have defined one of the following actions as the event that causes the system to go into hibernation mode, perform that action:
 - Closing the lid.
 - Pressing the power button.

Also, the computer goes into hibernation mode automatically in either of the following conditions:

- If a “hibernation time” has been set on the timer, and if the user does not do any operation with the keyboard, the hard disk drive, the parallel connector, or the diskette drive within that time.
- If the timer conditions are satisfied in suspend mode.

When the power is turned on, the computer returns from hibernation mode and resumes operation. The hibernation file in the boot record on the hard disk drive is read, and system status is restored from the hard disk drive.

Lenovo IdeaPad U160/U165

This chapter presents the following product-specific service references and product-specific parts information:

- “Specifications” on page 27
- “Status indicators” on page 29
- “Fn key combinations” on page 31
- “FRU replacement notices” on page 32
- “Removing and replacing an FRU” on page 33
- “Locations” on page 60
- “Parts list” on page 62

Specifications

The following table lists the specifications of the Lenovo IdeaPad U160/U165 :

Table 1. Specifications

Feature	Description
Processor	<ul style="list-style-type: none"> • U160: Intel Calpella ULV/CULV, Core 2 Duo, Celeron • U165: AMD Nile dual core and single core
Core Chipset	<ul style="list-style-type: none"> • U160: HM55 for Intel • U165: RS880M/SB820M for AMD
Bus architecture	<ul style="list-style-type: none"> • 667MHz FSB • 667MHz DDR2 SDRAM • PCI Express Bus • PCI Bus (not used) • DMI
Graphic memory chip	<ul style="list-style-type: none"> • U160: Intel GMA for Intel Platform • U165: ATI Mobility Radeon HD 4200 with optional 128MB LFB
Display	<ul style="list-style-type: none"> • 11.6" HD, White LED backlight, Flat type • 1366 x 768 resolution
Standard memory	<ul style="list-style-type: none"> • U160: Intel DDR3-1066 MHz 1x1GB slot, 2x1GB slot, 1x2GB slot • U165: AMD DDR3-1066MHz (actual running speed of 800 MHz) 1x1GB slot, 2x1GB slot, 1x2GB slot
CMOS RAM	<ul style="list-style-type: none"> • 256 bytes
Hard disk drive	<ul style="list-style-type: none"> • U160: 250/320/500GB, 5400rpm, 2.5" SATA • U165: 160/250/320/500GB, 5400rpm, 2.5" SATA
Optical drive	<ul style="list-style-type: none"> • Support USB external ODD

Table 1. Specifications (continued)

Feature	Description
I/O port	<ul style="list-style-type: none"> External monitor connector Stereo headphone jack Microphone jack RJ45 x 1 (on planar) USB2.0 x 2 (on planar) eSATA/USB combo port x 1 5-in-1 media card reader
MODEM slot	<ul style="list-style-type: none"> N/A
Audio	<ul style="list-style-type: none"> Headphone Jack x 1 Mic-In Jack x 1 Built-in Stereo Speakers, 2 x 1.5W with 6 cc chamber
Video	<ul style="list-style-type: none"> CRT port x 1 (on planar)
Ethernet (on the system board)	<ul style="list-style-type: none"> 10/100/1000 M Ethernet
PCI Express Mini Card slot	<ul style="list-style-type: none"> Wireless LAN MiniCard (PCIe) slot x 1(half size) Wireless WAN MiniCard (PCIe) slot x 1(full size)
Bluetooth wireless	<ul style="list-style-type: none"> Bluetooth module V2.1 Built-in antenna with min-USB interface, select Models
Keyboard	<ul style="list-style-type: none"> 260 mm width Keyboard
Touch pad	<ul style="list-style-type: none"> Two clicks and 1 LED indicator
Integrated camera	<ul style="list-style-type: none"> U160: 1.3M pixel U165: 0.3M pixel
Battery	<ul style="list-style-type: none"> 3 cells/6 cells cylinder battery, 2200mAH
AC adapter	<ul style="list-style-type: none"> U160: 20V/40W U165: 20V/65W
Pre-installed operating system	<ul style="list-style-type: none"> Windows 7 Home Starter (32bit) Windows 7 Home Basic (32bit) Windows 7 Home Basic (64bit) Windows 7 Home Premium (32bit) Windows 7 Home Premium (64bit) Free DOS

Status indicators

The system status indicators below show the computer status:




Table 2. Status indicators







Indicator	Meaning
<div>■</div> Caps lock 	White: Caps Lock mode is enabled. You can enter all alphabetic characters (A-Z) in uppercase without pressing the Shift key. To enable or disable Caps Lock mode, press the CapsLk key.
<div>■</div> Scroll lock 	White: Scroll Lock mode is enabled. To enable or disable Scroll Lock mode, press and hold the Fn key, and press the Delete(ScrLk) key.
<div>■</div> Power on 	White: System is enabled. Blinking white: System is in sleep mode. Off: System is in hibernate mode or shut down.

Table 2. Status indicators (continued)

Indicator	Meaning
4 Battery status 	<p>Blinking amber: (500ms off/1s on) The remaining power of the battery is less than 5% of its capacity.</p> <p>Blinking amber: (100ms off/3.2s on) The battery is being charged with the remaining power between 5% and 20% of its capacity.</p> <p>Amber: The computer is operating on battery power with the remaining power between 5% and 20% of its capacity.</p> <p>Blinking white: The battery is being charged with the remaining power between 20% and 80% of its capacity.</p> <p>White: The remaining power of the battery is more than 80% of its capacity, or the computer is operating on battery power with the remaining power between 20% and 80% of its capacity.</p>
5 Wireless status 	<p>White: Any one of the wireless devices (WLAN/Bluetooth/WWAN) is enabled.</p> <p>Off: All the wireless devices (WLAN/Bluetooth/WWAN) are disabled.</p>
6 Drive in use 	<p>White: Data is being read from or written to the hard disk drive. When this indicator is on, do not put the computer into standby mode or turn off the computer.</p> <p>Note: Do not move the system while the white drive-in-use light is on. Sudden physical shock could cause drive errors.</p>
7 Touchpad	<p>White: The touchpad is disabled. To enable or disable the touchpad, press and hold the Fn key, and press the F6 key.</p>

Fn key combinations

The following table shows the function of each combination of Fn with a function key.

Table 4. Fn key combinations

Key combination	Description
Fn + Esc:	Turn on/off the integrated camera.
Fn + F1:	Enter sleep mode.
Fn + F2:	Turn on/off the LCD screen.
Fn + F3:	Open the interface for the display device switch to select notebook or external display.
Fn + F5:	Open the interface for integrated wireless devices settings (enable/disable).
Fn + F6:	Enable/Disable the touchpad.
Fn + F7:	Start/Pause playback of Windows Media Player.
Fn + F8:	Stop playback of Windows Media Player.
Fn + F9:	Skip to the previous track.
Fn + F10:	Skip to the next track.
Fn + F11:	Activate the F12 function. * You can press Fn+F11 during computer startup to open the boot selection menu.
Fn + PrtSc:	Activate the system request.
Fn + Pause:	Activate the break function.
Fn + Delete:	Enable/Disable the Scroll Lock.
Fn + ↑/ ↓:	Increase/Decrease display brightness.
Fn + →/ ←:	Increase/Decrease volume level.

FRU replacement notices

This section presents notices related to removing and replacing parts. Read this section carefully before replacing any FRU.

Screw notices

Loose screws can cause a reliability problem. In the Lenovo IdeaPad computer, this problem is addressed with special nylon-coated screws that have the following characteristics:

- They maintain tight connections.
- They do not easily come loose, even with shock or vibration.
- They are harder to tighten.
- Each one should be used only once.


Do the following when you service this machine:

- Keep the screw kit in your tool bag.
- Always use new screws.
- Use a torque screwdriver if you have one.

Tighten screws as follows:


- **Plastic to plastic**

Turn an additional 90° after the screw head touches the surface of the plastic part:



- **Logic card to plastic**

Turn an additional 180° after the screw head touches the surface of the logic card:



- **Torque driver**

If you have a torque screwdriver, refer to the "Torque" column for each step.

- Make sure that you use the correct screws. If you have a torque screwdriver, tighten all screws firmly to the torque shown in the table. **Never use a screw that you removed. Use a new one. Make sure that all screws are tightened firmly.**
- Ensure torque screwdrivers are calibrated correctly following country specifications.

Removing and replacing an FRU

This section presents exploded figures with the instructions to indicate how to remove and replace the FRU. Make sure to observe the following general rules:

1. Do not attempt to service any computer unless you have been trained and certified. An untrained person runs the risk of damaging parts.
2. Before replacing any FRU, review "FRU replacement notices" on page 32.
3. Begin by removing any FRUs that have to be removed before the failing FRU. Any of such FRUs are listed at the top of the page. Remove them in the order in which they are listed.
4. Follow the correct sequence in the steps to remove the FRU, as given in the figures by the numbers in square callouts.
5. When turning a screw to replace an FRU, turn it in the direction as given by the arrow in the figure.
6. When removing the FRU, move it in the direction as given by the arrow in the figure.
7. To put the new FRU in place, reverse the removal procedures and follow any of the notes that pertain to replacement. For information about connecting and arranging internal cables, see "Locations" on page 60.
8. When replacing an FRU, use the correct screw as shown in the procedures.

DANGER

Before removing any FRU, turn off the computer, unplug all power cords from electrical outlets, remove the battery pack, and then disconnect any of the interconnecting cables.

Attention: After replacing an FRU, do not turn on the computer until you have made sure that all screws, springs, and other small parts are in place and none are loose inside the computer. Verify this by shaking the computer gently and listening for rattling sounds. Metallic parts or metal flakes can cause electrical short circuits.

Attention: The system board is sensitive to, and can be damaged by, electrostatic discharge. Before touching it, establish personal grounding by touching a ground point with one hand or using an electrostatic discharge (ESD) strap (P/N 6405959) to remove potential shock reasons.


1010 Battery pack

⚠ DANGER

Only use the battery specified in the parts list for your computer. Any other battery could ignite or explode.

Figure 1. Removal steps of battery pack

Unlock the battery release lever **1**. Holding the battery release lever in the unlocked position **2**, remove the battery pack in the direction shown by arrow **3**.



When installing: Install the battery pack along the slide rails of the slot. Then make sure that the battery release lever is in the locked position.


1020 Dummy card

For access, remove this FRU:

- “1010 Battery pack” on page 34

Figure 2. Removal steps of dummy card

Open the memory card slot cover in the direction shown by arrow **1**. Remove the dummy card in the direction shown by arrow **2**.




1030 SIM card

For access, remove this FRU:

- “1010 Battery pack” on page 34

Figure 3. Removal steps of SIM card

Push the SIM card in until you hear a click, and then pull the SIM card out in the direction shown by arrow **1**.




1040 Keyboard

For access, remove this FRU:

- “1010 Battery pack” on page 34

Figure 4. Removal steps of keyboard


Remove three screws ■.



Step	Screw (quantity)	Color	Torque
■	M2 × 2 mm, flat-head, nylok-coated (3)	Black	1.6 kgfcm

Figure 4. Removal steps of keyboard (continued)

Lift the keyboard a little, detach the connector in the direction shown by arrows **2** **3**, and then remove the keyboard **4**.



When installing: Make sure that the FPC connector is attached firmly.


1050 Base cover

For access, remove these FRUs in order:

- “1010 Battery pack” on page 34
- “1040 Keyboard” on page 37

Figure 5. Removal steps of base cover


Remove two screws **1** and one screw **2**.



Step	Screw (quantity)	Color	Torque
1	M2 × 5 mm, flat-head, nylok-coated (3)	White	1.6 kgfcm
2	M2 × 2.5 mm, flat-head, nylok-coated (1)	White	1.6 kgfcm

Figure 5. Removal steps of base cover (continued)

Remove eight screws **3** on the bottom. Remove the base cover in the direction shown by arrow **4**.



Step	Screw (quantity)	Color	Torque
3	M2 × 5 mm, flat-head, nylok-coated (8)	White	1.6 kgfcm

Note: Applying labels to the base cover


The new base cover FRU is shipped with a kit containing labels of several kinds. When you replace the base cover, you need to apply the following label:

The following labels need to be peeled off from the old base cover, and need to be put on the new base cover.

- a** PAINT Label
- b** PRC/MTM Label
- c** SYSTEM BARCODE Label
- d** LAN ID Label
- e** COA Label
- f** Rating Label
- g** Malaysia Homologation Label
- h** Malaysia Sirim Label (BT)
- i** WLAN Label (Bluetooth Label if without WLAN Label)
- j** Bluetooth Label
- k** Network Access License (for China)
- l** SAR Label for US/CA
- m** ENERGY SAVING Label

For some models, you also need to apply one or two FCC labels. Check the old base cover; if it has one or two FCC labels, find duplicates of them in the label kit and apply them to the new base cover.

For the location of each label, refer to the following figure:




1060 PCI Express Mini Card for wireless LAN/WAN

For access, remove these FRUs in order:

- “1010 Battery pack” on page 34
- “1020 Dummy card” on page 35
- “1040 Keyboard” on page 37
- “1050 Base cover” on page 39

Figure 6. Removal steps of PCI Express Mini Card for wireless LAN/WAN



Disconnect two wireless LAN cables (black, white) and two wireless WAN cables (red, blue) in the direction shown by arrows ■, and then remove two screws ■.


In step ■, unplug the jacks by using the removal tool antenna RF connector (P/N: 08K7159), or pick up the connectors with your fingers and gently unplug them in the direction shown by arrows.

Notes: wireless LAN card has 2 cables in step ■.
 wireless LAN card in some models may have 3 cables in step ■.
 wireless WAN card has 2 cables in step ■.

Step	Screw (quantity)	Color	Torque
2	M2 × 3 mm, flat-head, nylok-coated (2)	Black	1.6 kgfcm

Figure 6. Removal steps of PCI Express Mini Card for wireless LAN/WAN (continued)

Remove two cards in the direction shown by arrows **3**.



When installing:

- In models with a wireless LAN card that has two antenna connectors, plug the black cable (1st) (MAIN) into the jack labeled **1**, and the white cable (2nd) (AUX) into jack labeled **2** on the card.
- In models with a wireless LAN card that has three antenna connectors, plug the black cable (1st) (MAIN) into the jack labeled **1**, the grey cable (3rd) into jack labeled **3**, and the white cable (2nd) (AUX) into jack labeled **2** on the card.
- In models with a wireless WAN card that has two antenna connectors, plug the red cable into the jack labeled **MAIN**, and the blue cable into the jack labeled **AUX** on the card.


1070 LCD unit

For access, remove these FRUs in order:


- “1010 Battery pack” on page 34
- “1020 Dummy card” on page 35
- “1040 Keyboard” on page 37
- “1050 Base cover” on page 39
- “1060 PCI Express Mini Card for wireless LAN/WAN” on page 42

Figure 7. Removal steps of LCD unit

Remove the LCD connector ■ and release the LCD cable and antenna cables from the cable guides ■.




Remove two screws ■.




Step	Screw (quantity)	Color	Torque
3	M2 × 5 mm, flat-head, nylok-coated (2)	White	1.6 kgfcm

Figure 7. Removal steps of LCD unit (continued)

Swing the LCD hinges in the direction shown by arrows **4**.



Remove the LCD unit in the direction shown by arrow **5**.



1080 Hard disk drive (HDD)



For access, remove these FRUs in order:


- “1010 Battery pack” on page 34
- “1020 Dummy card” on page 35
- “1040 Keyboard” on page 37
- “1050 Base cover” on page 39
- “1060 PCI Express Mini Card for wireless LAN/WAN” on page 42
- “1070 LCD unit” on page 44


Attention:


- **Do not drop the hard disk drive or apply any physical shock to it.** The hard disk drive is sensitive to physical shock. Improper handling can cause damages and permanent loss of data.
- Before removing the drive, suggest the customer to backup all the information on it if possible.
- Never remove the drive while the system is operating or is in suspend mode.

Figure 8. Removal steps of hard disk drive

Note: Remove two screws  and then remove the hard disk drive in the direction shown by arrow .



Step	Screw (quantity)	Color	Torque
	M2 × 5 mm, flat-head, nylok-coated (2)	White	1.6 kgfcm




1090 DIMM

For access, remove these FRUs in order:

- “1010 Battery pack” on page 34
- “1020 Dummy card” on page 35
- “1040 Keyboard” on page 37
- “1050 Base cover” on page 39

Figure 9. Removal steps of DIMM

Release the two latches on both edges of the socket at the same time in the direction shown by arrows **1**, and then unplug the DIMM in the direction shown by arrows **2**.



When installing: Insert the notched end of the DIMM into the socket. Push the DIMM firmly, and pivot it until it snaps into the place. Make sure that it is firmly fixed in the slot and difficult to be moved.


1100 Fan assembly and heat sink assembly

For access, remove this FRU:

- “1010 Battery pack” on page 34
- “1020 Dummy card” on page 35
- “1040 Keyboard” on page 37
- “1050 Base cover” on page 39
- “1060 PCI Express Mini Card for wireless LAN/WAN” on page 42
- “1070 LCD unit” on page 44

Figure 10. Removal steps of fan assembly and heat sink assembly


Note: Loosen three screws **1**, but do not remove them. Detach the fan connector in the direction shown by arrow **2**.



When installing: Make sure that the fan connector is attached firmly to the system board.

Figure 10. Removal steps of fan assembly and heat sink assembly (continued)

Lift the fan assembly and heat sink assembly in the direction shown by arrow **3**. Be careful not to damage the connector.



When installing: Before you attach the fan assembly to the computer, apply thermal grease, at an amount of 0.2 grams, to the **a b** part shown in the figure above. Either too much or too less grease application can cause a thermal problem due to imperfect contact with a component.

1110 System board

Important notices for handling the system board:

When handling the system board, bear the following in mind.


- Be careful not to drop the system board on a bench top that has a hard surface, such as metal, wood, or composite.
- Avoid rough handling of any kind.
- In the whole process, make sure not to drop or stack the system board.
- If you put a system board down, make sure to put it only on a padded surface such as an ESD mat or conductive corrugated material.

For access, remove these FRUs in order:


- “1010 Battery pack” on page 34
- “1020 Dummy card” on page 35
- “1040 Keyboard” on page 37
- “1050 Base cover” on page 39
- “1060 PCI Express Mini Card for wireless LAN/WAN” on page 42
- “1070 LCD unit” on page 44
- “1080 Hard disk drive (HDD)” on page 46
- “1090 DIMM” on page 47
- “1100 Fan assembly and heat sink assembly” on page 48

Figure 11. Removal steps of system board

Detach two FPC connectors and one connector in the direction shown by arrows **1** **2**.



Remove three screws **3**, detach the speakers connector in the direction shown by arrow **4**.




When installing: Make sure that all the connectors are attached firmly.

Step	Screw (quantity)	Color	Torque
3	M2 × 5 mm, flat-head, nylok-coated (3)	White	1.6 kgfcm

Figure 11. Removal steps of system board (continued)

Remove the system board in the direction shown by arrow **5**.




1120 Speakers

For access, remove these FRUs in order:

- “1010 Battery pack” on page 34
- “1020 Dummy card” on page 35
- “1040 Keyboard” on page 37
- “1050 Base cover” on page 39
- “1060 PCI Express Mini Card for wireless LAN/WAN” on page 42
- “1070 LCD unit” on page 44
- “1080 Hard disk drive (HDD)” on page 46
- “1090 DIMM” on page 47
- “1100 Fan assembly and heat sink assembly” on page 48
- “1110 System board” on page 50


Figure 12. Removal steps of speakers

Remove two screws **1**, and release the cables from the cable guides **2**.



Step	Screw (quantity)	Color	Torque
1	M2 × 3 mm, flat-head, nylok-coated (2)	White	1.6 kgfcm

Remove the speakers in the direction shown by arrows **3**.




1130 Bluetooth card

For access, remove these FRUs in order:

- “1010 Battery pack” on page 34
- “1020 Dummy card” on page 35
- “1040 Keyboard” on page 37
- “1050 Base cover” on page 39
- “1060 PCI Express Mini Card for wireless LAN/WAN” on page 42
- “1070 LCD unit” on page 44
- “1080 Hard disk drive (HDD)” on page 46
- “1090 DIMM” on page 47
- “1100 Fan assembly and heat sink assembly” on page 48
- “1110 System board” on page 50

Figure 13. Removal steps of bluetooth card

Remove the bluetooth card in the direction shown by arrow **1**.





1140 LCD front bezel

For access, remove these FRUs in order:


- “1010 Battery pack” on page 34
- “1020 Dummy card” on page 35
- “1040 Keyboard” on page 37
- “1050 Base cover” on page 39
- “1060 PCI Express Mini Card for wireless LAN/WAN” on page 42
- “1070 LCD unit” on page 44


Figure 14. Removal steps of LCD front bezel

Remove two screws .



Step	Screw (quantity)	Color	Torque
	M2 × 3 mm, flat-head, nylok-coated (2)	Black	1.6 kgfcm

Remove the LCD front bezel in the direction shown by arrows .






1150 LCD panel, LCD cable and hinges

For access, remove these FRUs in order:

- “1010 Battery pack” on page 34
- “1020 Dummy card” on page 35
- “1040 Keyboard” on page 37
- “1050 Base cover” on page 39
- “1060 PCI Express Mini Card for wireless LAN/WAN” on page 42
- “1070 LCD unit” on page 44
- “1140 LCD front bezel” on page 55

Figure 15. Removal steps of LCD panel, LCD cable and hinges


Remove four screws  and then detach the hinges in the direction shown by arrows .



Step	Screw (quantity)	Color	Torque
	M2 × 3 mm, flat-head, nylok-coated (4)	Black	1.6 kgfcm

Figure 15. Removal steps of LCD panel, LCD cable and hinges (continued)

Remove four screws **3**, detach the integrated camera connector in the direction shown by arrow **4**, and then remove the LCD panel in the direction shown by arrows **5**.




Step	Screw (quantity)	Color	Torque
4	M2 × 3 mm, flat-head, nylok-coated (4)	Black	1.6 kgfcm

When installing: Make sure that the connector is attached firmly.

Note: The LCD cables are attached to the LCD panel by a metal connector.

Peel off the adhesive tape and detach the metal connector in the direction shown by arrow **6**.



When installing: Make sure that the metal connector is attached firmly.


1160 Integrated camera

For access, remove these FRUs in order:

- “1010 Battery pack” on page 34
- “1020 Dummy card” on page 35
- “1040 Keyboard” on page 37
- “1050 Base cover” on page 39
- “1060 PCI Express Mini Card for wireless LAN/WAN” on page 42
- “1070 LCD unit” on page 44
- “1140 LCD front bezel” on page 55
- “1150 LCD panel, LCD cable and hinges” on page 56

Figure 16. Removal steps of integrated camera

Note: The integrated camera is stuck on the top center of the LCD cover. Remove the integrated camera from the LCD cover in the direction shown by arrow ■.



When installing: Stick the integrated camera to the top center of the LCD cover and adjust the placement of it to make sure the connector is attached firmly.


1170 Antenna assembly and LCD cover

For access, remove these FRUs in order:

- “1010 Battery pack” on page 34
- “1020 Dummy card” on page 35
- “1040 Keyboard” on page 37
- “1050 Base cover” on page 39
- “1060 PCI Express Mini Card for wireless LAN/WAN” on page 42
- “1070 LCD unit” on page 44
- “1140 LCD front bezel” on page 55
- “1150 LCD panel, LCD cable and hinges” on page 56

Figure 17. Removal steps of antenna assembly and LCD cover

Peel off the adhesive tapes securing the antenna boards, release the cables from the cable guide, and then remove the antenna assembly in the direction shown by arrows **1**.




When installing: Route the antenna cables along the cable guides and secure the antenna boards with adhesive tapes. As you route the cables, make sure that they are not subjected to any tension. Tension could cause the cables to be damaged by the cable guides, or a wire to be broken.

Locations


Front view

- Integrated camera
 - 2 Built-in microphone
 - 3 Wireless module antennas
 - 4 System status indicators
- Note:** For the description of each indicator, see “Status indicators” on page 29.
- 5 Power button
 - 6 OneKey Rescue System button
 - 7 Touchpad
 - 8 IdeaPad lighting logo




Right-side view

- 1 Headphone jack
- 2 Microphone jack
- 3 Integrated wireless device switch
- 4 HDMI port
- 5 USB port
- 6 Kensington slot
- 7 RJ-45 port



Bottom and Left-side view

- 1 Memory card slot
- 2 Fan louvers
- 3 eSATA/USB combo port
- 4 VGA port
- 5 AC power adapter jack
- 6 Battery latch - manual
- 7 Battery pack
- 8 SIM card slot (selected models only)
- 9 Battery latch - spring loaded
- 10 Speakers



Parts list

This section presents the following service parts:

- “Overall” on page 63
- “LCD FRUs” on page 67
- “Keyboard” on page 69
- “Miscellaneous parts” on page 72
- “AC adapters” on page 73
- “Power cords” on page 74

Notes:

- Each FRU is available for all types or models, unless specific types or models are specified.

Overall




Table 5. Parts list—Overall

No.	FRU	FRU no.
1	LCD unit (see “LCD FRUs” on page 67.)	
2	Keyboard (see “Keyboard” on page 69.)	
3	LU16 TOUCH BUTTON BOARD INTEL	31044102
4	LU16 UPPER CASE INTEL W/TP&SPEAKER	31044120
5	LU16 LED BOARD	31044101
6	CPU assembly, Intel ARD 1.06G 4M I7-620UM C-2 BGA processor	102000820
6	CPU assembly, Intel ARD 1.06G 3M I5-520UM C-2 BGA processor	102000818
6	CPU assembly, Intel ARD 1.20G 4M I7-640UM C-2 BGA processor	102000817
6	CPU assembly, AMD T-K625 1.50G 2M C3 BGA processor	102000814
6	CPU assembly, AMD A-K325 1.30G 2M C3 BGA processor	102000813
6	CPU assembly, AMD A-K125 1.70G 1M C3 BGA processor	102000822
7	LU16 M/B W/INTEL 1.06G I5/HEATSINK	11012220
7	LU16 M/B W/INTEL 1.2G I7/HEATSINK	11012221
7	LU16 M/B W/INTEL 1.06G I7/HEATSINK	11012222
8	LU16 IO BOARD INTEL W/CABLE	11012218
9	WLAN card, 802.11a/g/n && 802.16e, Intel 6250NX MOW M PCIE NB HMC	20002321
9	WLAN card, 802.11a/g/n && 802.16e, Intel 6250GX MOW M PCIE NB HMC	20002388
9	WLAN card, 802.11 a/g/n, Intel 6200N MOW M PCIE NB HMC	20002324
9	WLAN card, 802.11 b/g/n(1*1), Gtc BCM4313 M 802.11N Wistron NB	20002362
9	WLAN card, 802.11 b/g/n(1*1), Cbt AR9285 HB95 BGN Wistron NB	20002343
9	WLAN card, 802.11 b/g/n(1*1), Liteon AR9285 HB95 BGN Wistron NB	20002353
9	WLAN card, 802.11 b/g/n(1*2), Intel 1000N MOW M PCIE NB HMC	20002329
9	WWAN card, WCDMA/HSDPA 7.2M, Ericsson F3607gw WCDMA 850MHz WWAN	11011296
9	WWAN card, WCDMA/HSDPA 7.2M, Ericsson F3607gw WCDMA 900MHz WWAN	11011295
9	WWAN card, WCDMA/HSDPA 7.2M, Huawei EM770 HSDPA MiniPCIE WWAN card	11010888
9	WWAN card, WCDMA/HSDPA 7.2M, Huawei EM770U WCDMA MOW WWAN card	11011654
9	WWAN card, WCDMA/HSDPA 7.2M, Huawei EM770W WCDMA MOW WWAN card	11011653
9	WWAN card, Gobi, Qualcomm GOBI WCDMA/EVDO WWAN Card	11011655
9	WWAN card, EVDO, Huawei EM660 EV-DO MiniPCIE WWAN card	11010853
9	WWAN card, EVDO, ZTE MC2716 EVDO MiniPCIE WWAN card	11011055
9	WWAN card, TD-SCDMA, TC LC5730D TD-SCDMA MiniPCIE WWAN card	11011652

Table 5. Parts list—Overall (continued)

No.	FRU	FRU no.
9	WWAN card, TD-SCDMA, TC LC5730C TD+CMMB MiniPCIE WWAN card	11011598
9	WWAN card, TD-SCDMA, LM TD231 TD-SCDMA MiniPCIE WWAN card	11011651
9	WWAN card, TD-SCDMA, LM TD232 TD+CMMB MiniPCIE WWAN card	11011650
9	WWAN card, TD-SCDMA, ZTE MU303 TD+CMMB MiniPCIE WWAN card	11011599
9	WWAN card, TD-SCDMA, ZTE MU302 TD-SCDMA MiniPCIE WWAN card	11011600
10	DDRIII 1066 1GB, M471B2873FHS-CF8	11011550
10	DDRIII 1066 1GB, EBJ10UE8BDS0-AE-F (Rev D /1Gb/65nm)	11011281
10	DDRIII 1066 1GB, MT8JSF12864HZ-1G1F1(V58B/1Gb/68nm)	11010924
10	DDRIII 1066 1GB, HYN HMT112S6TFR8C-G7N0 DDR3 1066 1GB	11011555
10	DDRIII 1066 2GB, M471B5673FH0-CF8	11011551
10	DDRIII 1066 2GB, EBJ21UE8BDS0-AE-F(Rev D /1Gb/65nm)	11011240
10	DDRIII 1066 2GB, MT16JSF25664HZ-1G1F1 (V58B/1Gb/68nm)	11010925
10	DDRIII 1066 2GB, HYN HMT125S6TFR8C-G7N0 DDR3 1066 2GB	11011554
10	DDRIII 1066 4GB, SAM M471B5273CH0-CF8 DDR3 1066 4GB	11011937
10	DDRIII 1066 4GB, HMT351S6AFR8C-G7N0 (Orion/2Gb/54nm)	11011215
10	DDRIII 1066 4GB, EBJ41UF8BAS0-DJ-F (Rev A /2Gb/50nm)	11011867
10	DDRIII 1333 1GB, SAM M471B2873FHS-CH9 DDR3 1333 1GB	11011936
10	DDRIII 1333 1GB, EBJ10UE8BDS0-DJ-F(Rev D /1Gb/65nm)	11011497
10	DDRIII 1333 1GB, MT8JSF12864HZ-1G4F1(V58B/1Gb/68nm)	11011494
10	DDRIII 1333 1GB, HMT112S6TFR8C-H9 N0 (CS Samples 2010.1.8)	11011971
10	DDRIII 1333 2GB, SAM M471B5673FH0-CH9 DDR3 1333 2GB	11011935
10	DDRIII 1333 2GB, EBJ21UE8BDS0-DJ-F(Rev D/1Gb/65nm)	11011496
10	DDRIII 1333 2GB, MT16JSF25664HZ-1G4F1(V58B/1Gb/68nm)	11011493
10	DDRIII 1333 2GB, HMT125S6TFR8C-H9 N0 (CS Samples 2009.12.24)	11011970
10	DDRIII 1333 4GB, SAM M471B5273CH0-CH9 DDR3 1333 4GB	11011934
10	DDRIII 1333 4GB, HMT351S6AFR8C-H9 N0 (Rev Orion / 2Gb/54nm)	11011513
10	DDRIII 1333 4GB, EBJ41UF8BAS0-DJ-F (Rev A/2Gb/50nm)	11011867
11	HDD, 250G 5400rpm SATA, Hitachi HTS545025B9A300 250G 9NB	16004060
11	HDD, 250G 5400rpm SATA, WD WD2500BEVT-24A23T0 5400RPM250G	16004524
11	HDD, 250G 5400rpm SATA, Seagate ST9250315AS 250G 9NB	16004186
11	HDD, 250G 5400rpm SATA, Toshiba MK2565GSX 5400RPM 250G	16004641
11	HDD, 320G 5400rpm SATA, Hitachi HTS545032B9A300 320G 9NB	16004059


Table 5. Parts list—Overall (continued)

No.	FRU	FRU no.
11	HDD, 320G 5400rpm SATA, WD WD3200BEVT-24A23T0 5400RPM320G	16004525
11	HDD, 320G 5400rpm SATA, Seagate ST9320325AS 320G 9NB	16004183
11	HDD, 320G 5400rpm SATA, Toshiba MK3265GSX 5400RPM 320G	16004642
11	HDD, 500G 5400rpm SATA, Hitachi HTS545050B9A300 500G 9NB	16004058
11	HDD, 500G 5400rpm SATA, WD WD5000BEVT-24A0RT0 5400RPM500G	16004526
11	HDD, 500G 5400rpm SATA, Seagate ST9500325AS 500G 9NB	16004189
11	HDD, 500G 5400rpm SATA, Toshiba MK5065GSX 5400RPM 500G	16004643
11	HDD, 320G 7200rpm SATA, Hitachi HTS725032A9A364 7200RPM320G	16004530
11	HDD, 320G 7200rpm SATA, WD WD3200BEKT 7200RPM 320G	16004639
11	HDD, 320G 7200rpm SATA, Seagate ST9320423AS 7200RPM320G 9NB	16004533
11	HDD, 500G 7200rpm SATA, Hitachi HTS725050A9A364 7200RPM500G	16004531
11	HDD, 500G 7200rpm SATA, Seagate ST9500420AS 7200RPM500G 9NB	16004532
12	Bluetooth card, BT2.1+EDR, Fcn BCM92070 BT2.1 EDR Flash U NB	20002266
12	Bluetooth card, BT2.1+EDR, USI BCM92070 BT2.1 EDR Flash U NB	20002326
13	Battery pack, 11.1V 3cell 2200 mAh, M3 SMP 3S1P 24Wh Pearl Red Li-ion Bty	121001019
13	Battery pack, 11.1V 3cell 2200 mAh, M3 SMP 3S1P 24Wh Deep Purple Li-ion Bty	121001020
13	Battery pack, 11.1V 6cell 4400 mAh, M3 SMP 3S2P 48Wh Pearl Red Li-ion Bty	121001017
13	Battery pack, 11.1V 6cell 4400 mAh, M3 SMP 3S2P 48Wh Deep Purple Li-ion Bty	121001018
13	Battery pack, 11.1V 3cell 2200 mAh, M3 Sanyo 3S1P 24Wh Pearl Red Li-ion Bty	121001025
13	Battery pack, 11.1V 3cell 2200 mAh, M3 Sanyo 3S1P 24Wh Deep Purple Li Bty	121001026
13	Battery pack, 11.1V 6cell 4400 mAh, M3 Sanyo 3S2P 48Wh Pearl Red Li-ion Bty	121001023
13	Battery pack, 11.1V 6cell 4400 mAh, M3 Sanyo 3S2P 48Wh Deep PurpleLi-ionBty	121001024
14	LU16 LOWER CASE BLACK	31044109
14	LU16 LOWER CASE Red	31044110
15	ODD, Zhi He EODLDW-560A RAMBO external ODD	25008159
15	ODD, HLDS GP20N RAMBO external ODD	25009828

LCD FRUs

In Lenovo IdeaPad U160/U165, there are following types of LCDs.

- “11.6-in. WXGA TFT”



11.6-in. WXGA TFT

Table 6. Parts list—11.6-in. WXGA TFT

No.	FRU	FRU no.
1	LU16 LCD BEZEL INTEL W/CAMERA HOLE	31044107
2	LU16 LCD BEZEL CAP	31044122
3	LCD panel, 11.6" Wedge Type LED, LGD LP116WH1-TLN1 HD G W LED1 N LCD	18004193
3	LCD panel, 11.6" Wedge Type LED, AUO B116XW02 V0 HD G W LED1 NB LCD	18004196
3	LCD panel, 11.6" Wedge Type LED, SMS LTN116AT03-L01 HD G W LED1 NB LCD	18004190
3	LCD panel, 11.6" Wedge Type LED, CMO N116B6-L02 HD G W LED1 NB LCD	18004189
3	LCD panel, 11.6" Flat Type LED, SMS LTN116AT04-L01 HD G F LED1 NB LCD	18004192
3	LCD panel, 11.6" Flat Type LED, AUO B116XW03 V0 HD G F LED1 NB LCD	18004198
3	LCD panel, 11.6" Flat Type LED, LGD LP116WH2-TLN1 HD G F LED1 NB LCD	18004195
3	LCD panel, 11.6" Flat Type LED, AUO B116XW01 V0 HW0A HD G LED1 NB LCD	18003796
4	LU16 LCD HINGE PACK INTEL L/R	31044112
5	LU16 LCD CABLE INTEL	31044104
6	LU16 CAMEAR 1.3M	31044124
6	LU16 CAMEAR 0.3M	31044155
7	LU16 LCD PANEL INTEL WWAN BLACK	31044114
7	LU16 LCD PANEL INTEL WLAN BLACK	31044115
7	LU16 LCD PANEL INTEL WWAN RED	31044116
7	LU16 LCD PANEL INTEL WLAN RED	31044117

Keyboard

Table 7. Parts list—Keyboard

Language				P/N
Frame 260 keyboard	Chicony	Black	Bulgarian	25010563
			International English	25010564
			Swiss	25010565
			Slovenian	25010566
			Slovak	25010567
			Icelandic	25010568
			Belgian	25010569
			Four Nordic countries	25010570
			Hungarian	25010571
			Hebrew	25010572
			Greek	25010573
			Dutch	25010574
			Czech	25010575
			Japanese	25010576
			Brazilian	25010577
			Arabic	25010578
			German	25010579
			French	25010580
			Russian	25010581
			Traditional Chinese	25010582
			Korean	25010678
			French&English	25010679
			Latin	25010680
			Portuguese	25010681
			Thai	25010682
			Turkish	25010683
			Spanish	25010684
			Italian	25010685
			U.K. English	25010686
			English	25010687
		White	Bulgarian	25010643
			International English	25010644
			Swiss	25010645
			Slovenian	25010646
			Slovak	25010647
			Icelandic	25010648
			Belgian	25010649
			Four Nordic countries	25010650
			Hungarian	25010651
			Hebrew	25010652
			Greek	25010653
			Dutch	25010654
			Czech	25010655
			Japanese	25010587

Table 7. Parts list—Keyboard (continued)

Language				P/N
Frame 260 keyboard (continued)	Chicony (continued)	White (continued)	Brazilian	25010588
			Arabic	25010589
			German	25010590
			French	25010591
			Russian	25010592
			Traditional Chinese	25010593
			Korean	25010594
			French&English	25010595
			Latin	25010596
			Portuguese	25010597
			Thai	25010598
			Turkish	25010599
			Spanish	25010600
			Italian	25010601
	ALPS	Black	U.K. English	25010602
			English	25010603
			Portuguese	25010606
			Bulgarian	25010607
			International English	25010608
			Swiss	25010609
			Slovenian	25010610
			Slovak	25010611
			Icelandic	25010612
			Belgian	25010613
			Four Nordic countries	25010614
			Hungarian	25010615
			Hebrew	25010616
			Greek	25010617
			Dutch	25010618
			Czech	25010619
			Japanese	25010620
			Brazilian	25010621
			Arabic	25010622
			German	25010623
			French	25010624
			French	25010624
			Russian	25010625
			Traditional Chinese	25010626
			Korean	25010627
			French&English	25010628
			Latin	25010629
			Thai	25010630
			Turkish	25010631
			Spanish	25010632
			Italian	25010633

Table 7. Parts list—Keyboard (continued)

Language				P/N
Frame 260 keyboard (continued)	ALPS (continued)	Black (continued)	U.K. English	25010634
			English	25010635
			Bulgarian	25010739
			International English	25010740
			Swiss	25010741
			Slovenian	25010658
			Slovak	25010659
			Icelandic	25010660
			Belgian	25010661
			Four Nordic countries	25010662
			Hungarian	25010663
			Hebrew	25010664
			Greek	25010665
			Dutch	25010666
			Czech	25010667
			Japanese	25010668
			Brazilian	25010669
			Arabic	25010670
			German	25010671
			French	25010672
			Russian	25010673
			Traditional Chinese	25010674
			Korean	25010675
			French&English	25010676
			Latin	25010677
			Portuguese	25010636
			Thai	25010637
			Turkish	25010638
			Spanish	25010639
			Italian	25010640
			U.K. English	25010641
			English	25010642

Miscellaneous parts

Table 8. Parts list—Miscellaneous parts

FRU	P/N
System miscellaneous parts:	
• (a) LU16 HDD BRACKET	31044111
• (b) LU16 LCD SCREW RUBBER	31044123
Cable miscellaneous parts:	
• (c) LU16 BLUETOOTH CABLE	31044106
Note: Italicized letters in parentheses are references to the exploded view in "Overall" on page 63 and "LCD FRUs" on page 67.	

AC adapters

Table 9. Parts list—3-pin AC adapters

FRU	P/N
65W, Delta ADP-65KH B adapter	36001646
65W, Liteon PA-1650-56LC adapter	36001651
65W, Chicony CPA-A065 20V3.25A adapter	36001792
65W, Brazil PA-1650-52LB adapter	36001714
40W, Brazil PA-1400-12LB adapter	36001715
40W, 3 PIN, Delta ADP-40NH B adapter	36001648
40W, 3 PIN, Liteon PA-1400-12LC adapter	36001653
40W, 3 PIN, HIPRO LN-A0403A3C adapter	36001672

Power cords

A Lenovo IdeaPad power cord for a specific country or region is usually available only in that country or region:

Table 10. Parts list—3-pin power cords

Region	P/N
CCC	145000602
• SSD YD-118-1+IEC53RVV+SSD-3-2B-1 1m	
CCC	145000600
• LINETEK PC323+RVV300/300+LS15 1m	
Argentina	145000599
• LINETEK LS15+H03VV-F+LP39 1m	
Danmark	145000598
• LINETEK LS15+H03VV-F+LP-38 1m	
Switzerland	145000597
• LINETEK LS15+H03VV-F+LP-37 1m	
Brazil	145000596
• LINETEK LS15 H03VV-F LP26A 1m	
Israel	145000595
• LINETEK LS15+H03VV-F+LP-41 1m	
UL	145000594
• LINETEK LP-30B + SPT-2 + LS15 1m	
UK	145000593
• LINETEK LP-61L+ H03VV-F+ LS15 1m	
Indian	145000592
• LINETEK PE-361+ H05VV-F+ LS15 1m	
Italy	145000591
• LINETEK LS15+H03VV-F+PE-336 1m	
Korea	145000590
• LINETEK LS15+H05VV-F+LP-E04A 1m	
Australia	145000589
• LINETEK LS15+H03VV-F+LP-23A 1m	
Taiwan	145000588
• LINETEK LS15+VCTF+LP-53 1m	
Japan	145000587
• LINETEK LS15+VCTF+LP-54 1m	
Africa	145000586
• LINETEK LS15+H03VV-F+PE-364 1m	
CE	145000585
• LINETEK LP-34+H03VV-F + LS15 1m	
CCC	145000568
• Longwell LSG-31+RVV300/300+LS-18 1m	
Argentina	145000567
• Longwell LP-24+H03VV-F+LS-18 1m	
Danmark	145000566
• Longwell LP-40+H03VV-F+LS-18 1m	
Switzerland	145000565
• Longwell LP-37+H03VV-F+LS-18 1m	

Table 10. Parts list—3-pin power cords (continued)

Region	P/N
Brazil	145000564
• Longwell LP-46+H03VV-F+LS-18 1m	
Israel	145000563
• Longwell LP-41+H03VV-F+LS-18 1m	
UL	145000562
• Longwell LP-30B+SPT-2 18AWG+LS-18 1m	
UK	145000561
• Longwell LP-61L+H03VV-F+LS-18 1m	
Indian	145000560
• Longwell LP-67+BIS+LS-18 1m	
Italy	145000559
• Longwell LP-22+H03VV-F+LS-18 1m	
Korea	145000558
• Longwell LP-486+KTLH03VV-F+LS-5 1m	
Australia	145000557
• Longwell LP-23A+LFC-3R+LS-18 1m	
Taiwan	145000556
• Longwell LP-71+VCTF+LS-33 1m	
Japan	145000555
• Longwell LP-54+VCTF+LS-18 1m	
Africa	145000554
• Longwell LP-39+H03VV-F+LS-18 1m	
CE	145000553
• Longwell LP-34A+H03VV-F+LS-18 1m	

Notices

Lenovo may not offer the products, services, or features discussed in this document in all countries. Consult your local Lenovo representative for information on the products and services currently available in your area. Any reference to a Lenovo product, program, or service is not intended to state or imply that only that Lenovo product, program, or service may be used. Any functionally equivalent product, program, or service that does not infringe any Lenovo intellectual property right may be used instead. However, it is the user's responsibility to evaluate and verify the operation of any other product, program, or service.

Lenovo may have patents or pending patent applications covering subject matter described in this document. The furnishing of this document does not give you any license to these patents.

LENOVO GROUP LTD. PROVIDES THIS PUBLICATION "AS IS" WITHOUT WARRANTY OF ANY KIND, EITHER EXPRESS OR IMPLIED, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF NON-INFRINGEMENT, MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE. Some jurisdictions do not allow disclaimer of express or implied warranties in certain transactions, therefore, this statement may not apply to you.

This information could include technical inaccuracies or typographical errors. Changes are periodically made to the information herein; these changes will be incorporated in new editions of the publication. Lenovo may make improvements and/or changes in the product(s) and/or the program(s) described in this publication at any time without notice.

The products described in this document are not intended for use in implantation or other life support applications where malfunction may result in injury or death to persons. The information contained in this document does not affect or change Lenovo product specifications or warranties. Nothing in this document shall operate as an express or implied license or indemnity under the intellectual property rights of Lenovo or third parties. All information contained in this document was obtained in specific environments and is presented as an illustration. The result obtained in other operating environments may vary.

Lenovo may use or distribute any of the information you supply in any way it believes appropriate without incurring any obligation to you.

Any references in this publication to non-Lenovo Web sites are provided for convenience only and do not in any manner serve as an endorsement of those Web sites. The materials at those Web sites are not part of the materials for this Lenovo product, and use of those Web sites is at your own risk.

Any performance data contained herein was determined in a controlled environment. Therefore, the result obtained in other operating environments may vary significantly. Some measurements may have been made on development-level systems and there is no guarantee that these measurements will be the same on generally available systems. Furthermore, some measurements may have been estimated through extrapolation. Actual results may vary. Users of this document should verify the applicable data for their specific environment.

Trademarks

The following terms are either registered trademarks or trademarks of Lenovo in the United States and/or other countries:

- Lenovo®
- Lenovo logo®
- IdeaPad®
- VeriFace®
- OneKey Rescue® (OneKey Recovery, OneKey Antivirus)
- APS®
- Power Express®
- Energy Management and ReadyComm®

The following terms are trademarks of Microsoft Corporation in the United States, other countries, or both:

- Windows®
- Windows Vista®
- Windows® 7

The following are trademarks of Intel Corporation or its subsidiaries in the United States, other countries, or both:

- Intel®
- Intel® Core™ 2 Duo

Other company, product, or service names may be the trademarks or service marks of others.